

GPRS Settings for SAMSUNG

Samsung S300 V200 S200 C100 S300M X430 P400

Samsung S500 E700 E100 X100A X600A

Samsung S300/V200/S200/C100/S300M/X430/P400

- Press 'Menu' and scroll down to Select "Fun Box" followed by "WAP Browser". The screen will display the following:

- Home
- Favorite
- http://
- Settings
- Clear Cache
- Then Select 'Settings'.

- Click on any one of the 'Profile' settings to set up to access Gprs service.

- After you have selected one of the 'Profile' the screen will display the following items for you to type in. Select each one of the following item settings and then key in the appropriate settings as shown below. Please take great care in keying the correct or selecting the correct input as shown.

- Profile name : MeroGprs
- Homepage URL : http://merowap.com
- Security : Non-secure
- IP Address : 192.168.19.15
- Bearer : GPRS
- User Name :
- Password :
- APN : mero

- Once you have keyed in the above information, you can then now start to access Gprs service. To access Merogprs go back to the 'Menu' and select 'WAP Browser' and then 'Home'. You will then be connected to homepage.

Samsung S500/E700/E100/X100A/X600A

- Press 'Menu' and Select "Fun Box" followed by "www services". The screen will

- display the following:

- Home
- Bookmark
- Go to URL
- Clear Cache
- Proxy settings
- Current settings
- Then Select 'Proxy Settings'. Click on any one of the 'Profile' settings to set up to access Gprs service.

- After you have selected one of the 'Profile' the screen will display the following items for you to type in. Select each one of the following item settings and then key in the appropriate settings as shown below. Please take great care in keying the correct or selecting the correct input as shown.

- Profile name: MeroGprs
- Select GPRS setting and key in the following:
- Gateway IP address: 192.168.19.15
- Gateway IP port: 9201
- APN: mero
- Login ID:
- Password:
- Homepage URL http://merowap.com
- Bearer: Choose GPRS only

- Once you have keyed in the above information, you can then now start to access homepage.

- To access MeroGprs, go back to the 'Menu' and select 'www services' and then "Home". You will then be connected to MeroGprs. If you have a few settings, go to "Funbox", select "www services", then go to "current proxy" and select MeroGprs.